



Cell Phone controlled: IOS&Android
The IR remote controller

Feature

1, The battery can last for 6-8 hours when all LED on after full charge, and can last for more than 9-13 hours on auto running mode. Up to 20 Hours with red color diode on, about 12 hours if other single color on. Results will vary based on brightness of LED

2, it is suggested to charge the battery for at least 4 hours, which will extend the life span of the battery.

Features:

1. With Built-in 2.4G Wireless DMX 512 Receiver (DA-WDMX-PCB)
2. Rechargeable Powered: 12V 12000mah
3. Perfect Match up with 2.4 Wireless DMX 512 Transmitter (DA-WDMX-LCD)
4. Wifi mode by phone controlled (down load "LED Wifi" software)
5. Lux: 6,500 @ 1m
6. Switching Power Supply
7. Two DMX channels : 6/10
8. Electronic Linear Dimmer: 0-100%
9. High speed Electronic Strobe: 0-20/S
10. 3-Pin DMX in and DMX out
11. Daisy Chain Power in and Power out
12. Led Digital Display Menu
13. One Bracket
14. Body Color: Black or White Selectable

Technical parameters

- Power supply: AC100V-240V
- Frequency: 50 Hz-60 Hz
- Power consumption: 72W
- Light source: 4x6in1 LED RGBWA+UV
- Lamp life: 6-10 ten thousand hrs
- LED angle: 30(±5) degree
- Color: 16.7 million kinds of color change
- Control channels: 6/10 chs
- Battery power& wireless DMX
- Wireless DMX512 protocol
- Built-in 2.4G wireless receiver/transmitter for wireless DMX operation
- Control mode: DMX512, master/slave, auto, sound active, wireless DMX
- Automatic model (by function button): color change, color strobe, color dimmer, and color gradual change/color jump change
- Operation menu: 4 digit digital LCD display
- Packing size: 185mm*185mm*200mm
- N.W: 2.5kg

