

RGB TL

LED Tube Light for photo and video



Tube Light TL X2 /X4

DMX Reference Guide

CHANNEL	VALUE	%	FUNCTION
1	0-255	0-100	Dimmer 0% to 100%
2	255	0-100	CCT 2800K-8000K
3	0-10	0-4	GREEN/MAGENTA Neutral/No Effect
	11-20	5-8	-100 Green
	21-119	9-47	-99 to -1 Green
	120-145	48-57	Neutral/No Effect
	146-244	58-96	+1 to +99 Green
	245-255	97-100	+100 Green
4	0-255	0-100	CROSSFADE CCT to RGBW
5	0-255	0-100	RED Intensity
6	0-255	0-100	Green Intensity
7	0-255	0-100	Blue Intensity
8	0-255	0-100	White Intensity
9	0-255	0-100	CROSSFADE CCT to HSI
10	0-255	0-100	HUE 0 to 359 Degrees
11	0-255	0-100	SAT 0 to Full Saturation

12	0-255	0-100	<p>CROSSFADE</p> <p>CCT to GEL</p>
13	0-5	0-1.9	GEL #1
	6-10	1.9-3.8	GEL #2

	250-255	98-100	GEL #48
14	0-10	0-3.9	<p>STROBE</p> <p>OFF</p>
	11-40	4.3-15.6	Random Slow
	41-70	16-27.4	Random Medium
	71-100	27.8-39.2	Random Fast
	101-255	39.6-100	1 flash/s to 25 flashes/s
15	0-5	0-1.9	<p>EFX</p> <p>OFF</p>
	6-29	2.3-11.3	EFX #1
	30-54	11.7-21.2	EFX #2

	230-255	90.2-100	EFX #10

Note:

This DMX reference guide has been compiled according to the test.

Information subject to change without prior notice if there is any later.

You can download the latest version of the DMX reference guide from www.mettlecorp.cn.